

433MHZ DC 12V RELÈ WIRELESS RF REMOTE CONTROL INTERRUPTORE TRASMETTITORE + RICEVITORE SET



Features:

Easy to install and easy to carry

With a slidable cover on the remote control

With a hook on the remote control

Use Learning coding, stable and reliable

The wireless signal can pass through walls, floors and doors

You can turn on or turn off the receiver with transmitter (remote control) from any place within a reliable distance

Operating Voltage: DC12V

Maximum Load: 10A

Operating Frequency: 433MHZ (in set)

Receiver Sensitivity: -100dBm

Encoding Type: learning code

Board Size: Approx. 5.3x3.1cm/ 2.09x1.22"

Output Working Way:

1. Jog: Pressing one button is working. Loosing your finger on the same button is stop. (need one channel switch and one buttons remote control)
2. Self-lock: Pressing one button for one time is working. Pressing the same button again is stop (need one channel switch and one buttons remote control)
3. Inter-lock: Pressing one button is working. Pressing another button is stop (need one channel switch and 2 buttons remote control)

4. Please notice that here is 1CH and 1 button wireless remote control. You can choose the self-lock or jog working/output way, you better choose jog or self-lock, so pressing the button is open, and pressing again is close, or pressing is open, and loosing finger is close

Learning and Remove Method:

1. Press the learning code. The indicator from on to off, loosen your finger, press any button of the remote control, the indicator flash 2 times and off. It mean you learn it successfully
2. It can learn more than 12 PCS 2262 or 1527 chip with the different code wireless remote control
3. Remove/ Clean: Press the learning button about 8 seconds, the indicator turn on to off, it means the information that you keep have been removed successfully

Package Included:

1 x Learning Code Receiver

1 x Remote Control