



1. CARICARE LA BATTERIA DEL GPS E INSERIRE LA SIM TELEFONICA **SENZA PIN**, LA SIM TELEFONICA DEVE AVERE UN PIANO **DATI E SMS**

2. INVIARE I SEGUENTI SMS AL NUMERO DELLA SIM:

- begin123456

IL GPS RISPONDE CON **BEGIN,CONFIG OK**

- apn123456 mobile.vodafone.it (nel caso di vodafone) altrimenti sostituire con il proprio

IL GPS RISPONDE CON **APN,CONFIG OK**

- lowbat123456 0

IL GPS RISPONDE CON **LOWBAT,CONFIG OK**

- Check123456

IL GPS RISPONDE CON UN RIASSUNTO DEI PARAMETRI DEL DISPOSITIVO DOVE È CONTENUTO ANCHE L'IMEI PER IL CONTROLLO TRAMITE IL SITO [www.secumore1818.com](http://www.secumore1818.com)

- Smslink123456

IL GPS RISPONDE CON LA POSIZIONE TRAMITE LINK SU GOOGLE MAPS

check123456

CHECK,Imei: [REDACTED] Apn:  
[mobile.vodafone.it](http://mobile.vodafone.it),IP:[REDACTED]  
[REDACTED],Cnum:,Gsm:100,itv:300,TZ:0,  
speed:0,0,WL:0,0,0,Vol:60,Gps:0

**ALTRI COMANDI:**

Default password 123456, use mobile phone to send SMS as below to tracker's phone number, " " means space Each command must reply " configure OK" means succeed. Check APN website <http://bigfun.tripod.co.uk/>

| Function                                     | Format      | SMS Command                                     |
|--|-------------|---|
| <b>Step 1 Set APN</b>                        | Format      | apn123456 localApn ApnName ApnPassword          |
|  | Eg.send SMS | apn123456 tim.br tim tim                        |
| <b>Step 2-Set IP Port:</b>                   | Eg.         | adminip123456 www.gps228.com 8989               |
| <b>Device Default GPS mode last 12 hours</b> |             | wkmd123456 2                                    |
| Open LBS mode last 65hours                   |             | wkmd123456 1                                    |
| Open Real time GPS mode last 6 hours         |             | wkmd123456 0                                    |
| Set center number to receive alarm           |             | centernum123456 user PhoneNumber                |
| Cancel center number                         |             | centernum123456                                 |
| Check device parameter status                |             | check123456                                     |
| Voice listen mode (Personal use)             |             | monitor123456                                   |
| Recover tracker Mode                         |             | tracker123456                                   |
| Activate Low battery alarm                   |             | lowbat123456 1                                  |
| Cancel Low battery                           |             | lowbat123456 0                                  |
| Initialize factory setup (No need use)       |             | begin123456(the command will erase all setting) |